

Juniper MX Bras

В даному розділі буду описувати свій досвід налаштування Juniper MX в ролі [BRASy](#).

На моїй практиці були налаштовані Juniper MX80 MX104 MX960, на останній моделі зупинились (провайдер на якого я працюю), отже всі приклади будуть взяті з нього, але на 95% вони сумісні з іншими моделями Juniper MX. Все залежить від версії прошивки роутера.

DHCP server

Глобальні налаштування DHCP сервера

```
set system services dhcp-local-server pool-match-order external-authority
set system services dhcp-local-server pool-match-order ip-address-first
set system services dhcp-local-server no-stale-timer-refresh
set system services dhcp-local-server stale-timer 30
```

QinQ DHCP server

Наступний блок це власне налаштування DHCP сервера. Рекомендую зразу записувати різні кейси в окремі групи - так легше розуміти

```
set system services dhcp-local-server group IPOE_QINQ authentication password PROVIDER
set system services dhcp-local-server group IPOE_QINQ authentication username-include delimiter "|"
set system services dhcp-local-server group IPOE_QINQ authentication username-include user-prefix IPOE_QINQ
set system services dhcp-local-server group IPOE_QINQ authentication username-include mac-address
set system services dhcp-local-server group IPOE_QINQ authentication username-include vlan-tags
set system services dhcp-local-server group IPOE_QINQ liveness-detection failure-action clear-binding
set system services dhcp-local-server group IPOE_QINQ liveness-detection method layer2-liveness-detection
transmit-interval 300
set system services dhcp-local-server group IPOE_QINQ liveness-detection method layer2-liveness-detection max-
```

```
consecutive-retries 3
set system services dhcp-local-server group IPOE_QINQ reconfigure clear-on-abort
set system services dhcp-local-server group IPOE_QINQ reconfigure attempts 5
set system services dhcp-local-server group IPOE_QINQ reconfigure timeout 5
set system services dhcp-local-server group IPOE_QINQ reconfigure token mx960_0
set system services dhcp-local-server group IPOE_QINQ overrides client-discover-match incoming-interface
set system services dhcp-local-server group IPOE_QINQ dynamic-profile dhcp-profile
set system services dhcp-local-server group IPOE_QINQ access-profile IPOE_QINQ
set system services dhcp-local-server group IPOE_QINQ interface ae1.0
```

в даному блоці є 3 змінні без яких нічого не запрацює:

- dynamic-profile dhcp-profile
- access-profile IPOE_QINQ
- interface ae1.0

їх треба описати

dynamic-profile dhcp-profile

```
set dynamic-profiles dhcp-profile routing-instances "$junos-routing-instance" interface "$junos-interface-name"
set dynamic-profiles dhcp-profile interfaces demux0 unit "$junos-interface-unit" actual-transit-statistics
set dynamic-profiles dhcp-profile interfaces demux0 unit "$junos-interface-unit" no-traps
set dynamic-profiles dhcp-profile interfaces demux0 unit "$junos-interface-unit" proxy-arp
set dynamic-profiles dhcp-profile interfaces demux0 unit "$junos-interface-unit" demux-options underlying-
interface "$junos-underlying-interface"
set dynamic-profiles dhcp-profile interfaces demux0 unit "$junos-interface-unit" targeted-distribution
set dynamic-profiles dhcp-profile interfaces demux0 unit "$junos-interface-unit" family inet demux-source $junos-
subscriber-ip-address
set dynamic-profiles dhcp-profile interfaces demux0 unit "$junos-interface-unit" family inet unnumbered-address
"$junos-loopback-interface"
```

access-profile IPOE_QINQ

```
set access profile IPOE_QINQ accounting-order radius
set access profile IPOE_QINQ authentication-order radius
set access profile IPOE_QINQ domain-name-server 10.10.10.5
set access profile IPOE_QINQ domain-name-server 10.10.10.6
set access profile IPOE_QINQ radius authentication-server 10.10.10.7
set access profile IPOE_QINQ radius accounting-server 10.10.10.7
set access profile IPOE_QINQ radius options calling-station-id-delimiter *
set access profile IPOE_QINQ radius options calling-station-id-format mac-address
set access profile IPOE_QINQ radius options calling-station-id-format stacked-vlan
set access profile IPOE_QINQ radius options calling-station-id-format vlan
set access profile IPOE_QINQ radius options accounting-session-id-format decimal
set access profile IPOE_QINQ radius options client-authentication-algorithm round-robin
set access profile IPOE_QINQ radius options client-accounting-algorithm round-robin
set access profile IPOE_QINQ accounting order radius
set access profile IPOE_QINQ accounting immediate-update
set access profile IPOE_QINQ accounting coa-immediate-update
set access profile IPOE_QINQ accounting address-change-immediate-update
set access profile IPOE_QINQ accounting update-interval 10
set access profile IPOE_QINQ accounting statistics volume-time
set access profile IPOE_QINQ accounting wait-for-acct-on-ack
set access profile IPOE_QINQ accounting send-acct-status-on-config-change
```

```
set access radius-server 10.10.10.7 port 1812
set access radius-server 10.10.10.7 accounting-port 1813
set access radius-server 10.10.10.7 dynamic-request-port 3799
set access radius-server 10.10.10.7 secret "superhardpass:)"
set access radius-server 10.10.10.7 retry 3
set access radius-server 10.10.10.7 accounting-retry 3
set access radius-server 10.10.10.7 max-outstanding-requests 2000
set access radius-server 10.10.10.7 source-address *.*.*.*.2
```

Всі пули іп адрес, які можуть бути видані абоненту потрібно описати наступним чином

```
set access address-assignment pool cvlan10_128-17 family inet network 10.10.128.0/17
set access address-assignment pool cvlan10_128-17 family inet range ip low 10.10.128.11
set access address-assignment pool cvlan10_128-17 family inet range ip high 10.10.255.254
set access address-assignment pool cvlan10_128-17 family inet dhcp-attributes maximum-lease-time 10000
set access address-assignment pool cvlan10_128-17 family inet dhcp-attributes grace-period 100
set access address-assignment pool cvlan10_128-17 family inet dhcp-attributes router 10.10.128.2
### access address-assignment pool cvlan10_128-17 family inet dhcp-attributes option 43 hex-string 010400000002

set interfaces lo0 unit 0 family inet address 10.10.128.2/32
```

перші 10 іп з кожного пулу я резервую для майбутніх БРАСів. В мене використовується QinQ технологія, тому немає сенсу робити пули меншими - описую весь пул за раз.

```
set interfaces ael description ael
set interfaces ael flexible-vlan-tagging
set interfaces ael auto-configure stacked-vlan-ranges dynamic-profile Auto-VLAN-Stacked-Demux accept dhcp-v4
### interfaces ael auto-configure stacked-vlan-ranges dynamic-profile Auto-VLAN-Stacked-Demux accept pppoe
set interfaces ael auto-configure stacked-vlan-ranges dynamic-profile Auto-VLAN-Stacked-Demux ranges 501-515,any
set interfaces ael auto-configure remove-when-no-subscribers
set interfaces ael mtu 9216
set interfaces ael encapsulation flexible-ethernet-services
set interfaces ael aggregated-ether-options lacp active
set interfaces ael aggregated-ether-options lacp periodic fast
```

```
set dynamic-profiles Auto-VLAN-Stacked-Demux routing-instances "$junos-routing-instance" interface "$junos-interface-name"
set dynamic-profiles Auto-VLAN-Stacked-Demux interfaces demux0 unit "$junos-interface-unit" no-traps
set dynamic-profiles Auto-VLAN-Stacked-Demux interfaces demux0 unit "$junos-interface-unit" proxy-arp
set dynamic-profiles Auto-VLAN-Stacked-Demux interfaces demux0 unit "$junos-interface-unit" vlan-tags outer "$junos-stacked-vlan-id"
set dynamic-profiles Auto-VLAN-Stacked-Demux interfaces demux0 unit "$junos-interface-unit" vlan-tags inner "$junos-vlan-id"
```

```
set dynamic-profiles Auto-VLAN-Stacked-Demux interfaces demux0 unit "$junos-interface-unit" demux-options
underlying-interface "$junos-interface-ifd-name"
set dynamic-profiles Auto-VLAN-Stacked-Demux interfaces demux0 unit "$junos-interface-unit" family inet mac-
validate strict
set dynamic-profiles Auto-VLAN-Stacked-Demux interfaces demux0 unit "$junos-interface-unit" family inet
unnumbered-address "$junos-loopback-interface"
### dynamic-profiles Auto-VLAN-Stacked-Demux interfaces demux0 unit "$junos-interface-unit" family pppoe access-
concentrator PPPoE-Server
### dynamic-profiles Auto-VLAN-Stacked-Demux interfaces demux0 unit "$junos-interface-unit" family pppoe
duplicate-protection
### dynamic-profiles Auto-VLAN-Stacked-Demux interfaces demux0 unit "$junos-interface-unit" family pppoe dynamic-
profile PP0
```

- не хороша ідея на одному влані тримати і pppoe і dhcp абонів - dual-access на роутерах вам почнуть снитись в страшних снах

DHCP_SVLAN

```
set access profile BILLING accounting-order radius
set access profile BILLING authentication-order radius
set access profile BILLING radius authentication-server 172.20.20.1
set access profile BILLING radius accounting-server 172.20.20.1
set access profile BILLING radius options calling-station-id-delimiter *
set access profile BILLING radius options calling-station-id-format mac-address
set access profile BILLING radius options calling-station-id-format stacked-vlan
set access profile BILLING radius options calling-station-id-format vlan
set access profile BILLING radius options accounting-session-id-format decimal
set access profile BILLING radius options client-authentication-algorithm round-robin
set access profile BILLING radius options client-accounting-algorithm round-robin
set access profile BILLING accounting order radius
set access profile BILLING accounting immediate-update
set access profile BILLING accounting coa-immediate-update
set access profile BILLING accounting address-change-immediate-update
```

```
set access profile BILLING accounting update-interval 10
set access profile BILLING accounting statistics volume-time
set access profile BILLING accounting wait-for-acct-on-ack
set access profile BILLING accounting send-acct-status-on-config-change
```

```
set dynamic-profiles CLIENTS_SVLAN routing-instances "$junos-routing-instance" interface "$junos-interface-name"
set dynamic-profiles CLIENTS_SVLAN interfaces demux0 unit "$junos-interface-unit" actual-transit-statistics
set dynamic-profiles CLIENTS_SVLAN interfaces demux0 unit "$junos-interface-unit" no-traps
set dynamic-profiles CLIENTS_SVLAN interfaces demux0 unit "$junos-interface-unit" proxy-arp
set dynamic-profiles CLIENTS_SVLAN interfaces demux0 unit "$junos-interface-unit" demux-options underlying-
interface "$junos-underlying-interface"
### dynamic-profiles CLIENTS_SVLAN interfaces demux0 unit "$junos-interface-unit" targeted-distribution
set dynamic-profiles CLIENTS_SVLAN interfaces demux0 unit "$junos-interface-unit" family inet demux-source
$junos-subscriber-ip-address
set dynamic-profiles CLIENTS_SVLAN interfaces demux0 unit "$junos-interface-unit" family inet unnumbered-address
"$junos-loopback-interface"
set dynamic-profiles CLIENTS_SVLAN interfaces demux0 unit "$junos-interface-unit" family inet unnumbered-address
preferred-source-address $junos-preferred-source-address
```

```
set system services dhcp-local-server pool-match-order external-authority
set system services dhcp-local-server pool-match-order ip-address-first
set system services dhcp-local-server group DHCP_SVLAN authentication password IPoE-Pool
set system services dhcp-local-server group DHCP_SVLAN authentication username-include delimiter "|"
set system services dhcp-local-server group DHCP_SVLAN authentication username-include user-prefix IPOE_SVLAN
set system services dhcp-local-server group DHCP_SVLAN authentication username-include mac-address
set system services dhcp-local-server group DHCP_SVLAN authentication username-include vlan-tags
set system services dhcp-local-server group DHCP_SVLAN reconfigure clear-on-abort
set system services dhcp-local-server group DHCP_SVLAN reconfigure attempts 5
set system services dhcp-local-server group DHCP_SVLAN reconfigure timeout 5
set system services dhcp-local-server group DHCP_SVLAN reconfigure token mx104_0
### system services dhcp-local-server group DHCP_SVLAN overrides client-discover-match incoming-interface
set system services dhcp-local-server group DHCP_SVLAN dynamic-profile CLIENTS_SVLAN
set system services dhcp-local-server group DHCP_SVLAN access-profile RADIUS_SVLAN
set system services dhcp-local-server group DHCP_SVLAN interface demux0.802
```

```
set system services dhcp-local-server no-stale-timer-refresh
set system services dhcp-local-server stale-timer 30
```

From:
<https://ndp.pp.ua/> - **my NoDeny Wiki**

Permanent link:
https://ndp.pp.ua/doku.php/juniper/mx_bras?rev=1657379495

Last update: **09/07/2022 15:11**

